

EL465781620

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

APPLICATION FOR LETTERS PATENT

* * * * *

**INTEGRATED TELECOMMUNICATIONS CABINET
SYSTEM WITH DSX ASSEMBLIES AND
MULTIPLEXERS**

* * * * *

INVENTORS

**Jim Vercruyssen
Peter Mohr
Jon Thorpe**

ATTORNEY'S DOCKET NO. TE2-084

INTEGRATED TELECOMMUNICATIONS CABINET SYSTEM WITH DSX ASSEMBLIES AND MULTIPLEXERS

TECHNICAL FIELD

[0001] This invention relates to a cabinet system for use in telecommunications which includes both digital cross-connect connections and multiplexer connections in a single cabinet.

BACKGROUND OF THE INVENTION

[0002] With the large increase in demand for telecommunications capacity, there is an increasing need for greater density and capacity in all areas of telecommunications, including signal transmission, connections or cross-connections, and terminations. The better utilization of a given amount of space in telecommunications facilities is becoming more and more important.

[0003] In many facilities there are bays or racks in which different types of cabinets and other equipment are mounted. In the prior art example illustrated in Figure 1 for instance, there is a typical rack configuration which requires digital signal cross-connects ("DSX") jack assemblies and also requires multiplexers, sometimes designated as M13's (sometimes also referred to as "MUX").

[0004] Multiplexers are devices which facilitate the transmission of two or more signals over a single line, such as by time-division multiplexing or wavelength-division multiplexing. In multiplexing, the term or designation "M13" indicates a multiplexer/demultiplexer for DS1 to DS3 signals. A

DSX-1 is a digital signal cross-connect for electrical T1 or DS1 (digital signal 1 transmission rate, 1.544 Mb/s) transmission signals. A DSX-3 is a digital signal cross-connect for electrical T3 or DS3 (digital signal 3 transmission rate, 44.736 Mb/s) transmission signals. E1 is a European signal transmission rate of 2.048 Mb/sec, and there are generally twenty-one E1's in a T3. It should be noted that this invention is not limited to any one transmission standard or rate.

[0005] DSX assemblies are typically used for the electrical connection between cables in a central office, for cross-connecting and for the termination of lines at various locations.

[0006] Figure 1 illustrates a perspective view of a prior art configuration which includes a separate multiplexer cabinet 100 mounted near a separate DSX-1 cabinet 101. The multiplexer cabinet 100 includes at least one multiplexer 102 mounted therein and the DSX-1 cabinet 101 configuration includes a plurality of DSX-1 bantam jack assemblies 103 therein. In a typical prior art application, a multiplexer cabinet 100 would be mounted near a separate DSX-1 cabinet 101 to provide the multiplexing capability for the DSX-1 circuits. The multiplexer cabinet 100 and the DSX-1 cabinet 101 would typically be provided with the adapter hardware to be mounted to the desired location, such as an industry standard rack. There may also be a separate DSX-3 cabinet above the two shown in Figure 1, requiring even further additional space.

[0007] Since the respective cabinets shown in Figure 1 are dedicated to either DSX-1 circuits or jack assemblies 103 or M13 circuits 102, they

must be mounted near one another and are typically hard wired to one another. One of ordinary skill in the art will appreciate the desire to increase circuit density and minimize vertical rack space in facilities and in applications which require both DSX-1 circuits and M13 or other multiplexer components.

[0008] It is also desired to reduce the amount of time required to wire together DSX jack assemblies to multiplexers and providing an integrated system accomplishes this.

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218
2219
2220
2221
2222
222

BRIEF DESCRIPTION OF THE DRAWINGS

[0009] Preferred embodiments of the invention are described below with reference to the following accompanying drawings.

[0010] Figure 1 is a perspective view of a prior art configuration which includes a separate multiplexer cabinet and a separate DSX-1 cabinet;

[0011] Figure 2 is a perspective view of an embodiment of this invention which includes fifty-six DSX-1 jack assemblies and four (preferably two active and two standby) multiplexers, the four multiplexers being in the middle of the first end of the cabinet framework;

[0012] Figure 3 is a perspective view of an embodiment of this invention which includes fifty-six DSX-1 jack assemblies and four multiplexers, with two multiplexers being on each outward side of the first end of the cabinet framework;

[0013] Figure 4 is a perspective view of an embodiment of this invention which includes DSX-1 jack assemblies, DSX-3 assemblies and four multiplexers, with two multiplexers being on each outward side of the first end of the cabinet framework;

- [0014] Figure 5 is a perspective view of an embodiment of this invention which includes DSX-1 jack assemblies and four multiplexers, the multiplexers being configured within the cabinet but above the DSX-1 assemblies;
- [0015] Figure 6 is a functional block diagram of the cabinet system components of one embodiment of a cabinet system contemplated by this invention;
- [0016] Figure 7 is a system block diagram of the cabinet system components of one embodiment of a cabinet system contemplated by this invention;
- [0017] Figure 8 is a diagram of the relationship of Figures 9 - 11, which is an electrical block diagrams of one embodiment of a cabinet system contemplated by the invention;
- [0018] Figure 9 is an electrical block diagram of the cabinet system components of one embodiment of a cabinet system contemplated by this invention, as depicted in Figure 8;
- [0019] Figure 10 is an electrical block diagram of the cabinet system components of one embodiment of a cabinet system contemplated by this invention, as depicted in Figure 8;
- [0020] Figure 11 is an electrical block diagram of the cabinet system components of one embodiment of a cabinet system

contemplated by this invention, as depicted in Figure 8; and

[0021] Figure 12 is a perspective view of an embodiment of this invention which includes DSX-3 assemblies and four multiplexers, with two multiplexers being on each outward side of the first end of the cabinet framework.

Figure 12

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

[0022] Many of the fastening, connection, manufacturing and other means and components utilized in this invention are widely known and used in the field of the invention described, and their exact nature or type is not necessary for an understanding and use of the invention by a person skilled in the art or science; therefore, they will not be discussed in significant detail. Furthermore, the various components shown or described herein for any specific application of this invention can be varied or altered as anticipated by this invention and the practice of a specific application or embodiment of any element may already be widely known or used in the art or by persons skilled in the art or science; therefore, each will not be discussed in significant detail.

[0023] The terms "a", "an", and "the" as used in the claims herein are used in conformance with long-standing claim drafting practice and not in a limiting way. Unless specifically set forth herein, the terms "a", "an", and "the" are not limited to one of such elements, but instead mean "at least one".

[0024] The term "framework" as used herein need not be continuous or in any specific number of pieces. However it will be appreciated by those skilled in the art that the framework could be one piece, two piece or more than two pieces. Furthermore, the framework as contemplated by this invention need not be in one continuous section, but instead may also be divided up into multiple sections or segments.

[0025] The DSX portion of the cabinet system may be a cabinet with modules such as those disclosed in commonly owned U.S. Patent Numbers 4,975,087 and 5,938,478, both of which are hereby incorporated herein by this reference as though fully set forth herein.

[0026] The term plurality of jack assemblies as used herein is intended to cover a plurality of jack circuits, and/or a plurality of columns of sleeves disposed to receive jack plugs, whether the front panel is one piece with the front panels of adjacent jack assemblies. Thus a one piece front panel with a plurality of jack circuits and/or a plurality of columns of sleeves, is a plurality of jack assemblies as used herein. The jack assemblies may also be single circuit replaceable, although the invention is not limited to any one type of DSX assembly or configuration in particular.

[0027] The term DS1 (or T1) generally refers to a digital signal 1 transmission at a rate of 1.544 Mb/s and the term DS3 generally refers to a digital signal 3 transmission at a rate of 44.736 Mb/s, both of which are well known in the industry. The term "mux" is well known in the art and generally refers to multiplexers. The term M13 or M13 or "1-3 mux" is also well known and generally refers to multiplexers for DS1 to DS3 signals. The term DSX generally refers to "Digital Signal Cross-Connects" and a DSX-1 is a digital signal cross-connect for DS1 signals. T1 is also referred to as Digital Signal Level One (DS1), which is a standard for high-speed digital transmission. T1 facilities generally operate at 1.544 Mbps,

the equivalent of twenty-four - 64kbps channels (DS0 or Digital Signal Level 0 channels). T3 is twenty-eight T1's running at 44.736 Mb/second.

[0028] Some embodiments of this invention generally include a combination of DS1 digital cross-connects with DS1 or DS3 multiplexing (1-3 mux or M13). In one embodiment, fifty-six DSX module and one or two M13's can be installed in what is known as a single nineteen inch wide and five and one-quarter inch tall size unit, in a cabinet or framework configuration.

[0029] There are numerous alternative embodiments and configurations within the contemplation of this invention, for example but without limitation, embodiments which interface with high speed DS3 connections, or with fiber optical broadband connections. Additional features may be included in the invention, such as DS0 grooming. DS0 is Digital Signal level 0, 64 kbps or 64,000 bits per second. There are twenty four DS-0's in a DS1.

[0030] Preferred cabinet framework dimensions allow the cabinet framework to fit on industry standard rack lengths, an example of which is generally referred to as a nineteen inch rack. It should be noted however that the rack may be any one of a number of different desirable or standard sizes, such as what is generally referred to as a twenty-three inch rack as well, with the invention not being limited to any one in particular. For the standard nineteen inch rack, the cabinet framework dimensions may be seventeen and thirty-eight one-hundredths wide, five and two-tenths high and twelve inches in first end to second end depth. The increased density for the components provided by this embodiment of the invention

would be one to four M13 and fifty-six DSX-1 jack assemblies in less than five and one-quarter inches of vertical rack space or height in what is referred to as a nineteen inch wide rack. The cabinet framework may be configured to be mounted in any one of a number of different ways, preferably to customer racks via rack mounting adapters which are generally known and used in the industry.

[0031] It will be appreciated by those skilled in the art that this component density, as compared to the prior art (Figure 1), yields significantly higher density for a fifty-six circuit DSX-1 with M13 capability.

[0032] It will also be appreciated by those of ordinary skill in the art that the invention may be provided not only with one or two active M13's, but also with one or two standby M13's.

[0033] The DSX cabinet may be any one of a number of different cabinets with bantam jack modules, such as those disclosed in U.S. Patent Numbers 4,975,087 or 5,938,478, to name a few.

[0034] In a typical application, one multiplexer may be used for approximately twenty-eight DSX-1 circuits and two multiplexers for fifty-six DSX-1 circuits.

[0035] The backplane termination configuration includes four sixty-four (64) pin "D" style or type connectors, two RJ45 connectors, four BNC connectors, two power/return connectors, one dual chassis ground stud, four drain wire ground studs and two dry alarm connectors. No particular backplane termination configuration is required to practice this invention as

there are numerous configurations within the contemplation of this invention. Wire cable management provisions may also be provided.

[0036] Embodiments of the invention further include a dual M13 with a built-in fifty-six circuit DSX panel. The M13 will allow twenty-eight dedicated DS1 channels to be multiplexed into one DS3 channel. Examples of some alternative embodiments and/or alternative product configurations, within the contemplation of this invention may include: single M13 with a DSX panel (DSX-1 and/or DSX3); dual M13's with independent DSX panels; or a single M13 with a dual DSX panel, to name a few.

[0037] System embodiments within the contemplation of this invention allow the user flexibility to expand for increased bandwidth. For instance, a user with a configuration with only one M13 with a single DSX panel may later add an additional M13 by merely adding the additional components to the cabinet framework, allowing the user to increase the bandwidth of the system.

[0038] The term backplane interconnect conductor as used herein generally refers to the conductor or series of conductors which electrically connect the plurality of DSX-1 jack assemblies and the at least one multiplexer to the backplane printed circuit board assembly, and may be a printed circuit board, a connector ribbon, or any one of a number of other individual or combined components which may be used to electrically connect the components.

[0039] Figure 2 is a perspective view of an embodiment of this cabinet system invention, illustrating cabinet framework 120, first end 120a, second

end 120b, and side walls 120c. Figure 2 illustrates two sets of DSX-1 jack assemblies 130 and 134, with the preferred number being twenty-eight jack assemblies per set (although no specific number of either jack assemblies or multiplexers, are required to practice this invention). It should be noted that the first end 120a will generally be the front end or the aisle end, whereas the second end will generally be the rear end opposite end.

[0040] The DSX-1 jack assemblies 130 and 134 are well known in the industry and any one of a number of different types or kinds may be utilized within the contemplation of this invention, with no one in particular being required to practice the invention. Two exemplary jack assemblies are those disclosed in U.S. Patent Numbers 4,975,087 and 5,938,478, as incorporated by reference elsewhere herein. DSX-3 assemblies are also well known and an exemplary assembly is disclosed in U.S. Patent Number 5,233,501, which is hereby incorporated herein by this reference.

[0041] The jack assemblies 130 and 134 may but need not includes LED indicators 141 and 140, as are well known in the industry. The jack assemblies include switch assemblies and are preferably of the front access type, with terminal pin connector fields 132 being at the first end of the jack assemblies. The jack assemblies or circuits may also be what is generally referred to as "rear access" meaning the circuits are generally accessed from the rear end of the cabinet.

[0042] One jack assembly generally includes one circuit, which is well known in the art, and when reference is made herein to fifty-six or forty-two jack assemblies, this may also mean circuits and should include circuits

if the jack assemblies are somehow combined. The cross-connect field may be wire-wrap pins, insulation displacement connectors ("IDC"), RJ-48 jacks, or others.

[0043] The jack assemblies 132 and 140 may be connected to the rear or backplane printed circuit board assembly 123 by any one of a number of different types of electrical conductors, such as ribbon cable, backplane interconnect boards 125 and 131, or in other ways.

[0044] The backplane printed circuit board assembly may be one continuous board, two independent boards, one for each set of jack assemblies and multiplexers, or even physically independent and individual boards, with many being known in the art. In this case the preferred way is one printed circuit board 123 with the typical rear connectors utilized with DSX-1 jack assemblies, such as terminal pin connectors, DS3 connectors, and the like.

[0045] The DSX-1 jack assemblies would typically include, for example a monitor sleeve 145, an input sleeve 143 and an output sleeve 144, all as are known in the art.

[0046] The multiplexers, namely first set 121 and second set 126 of multiplexer, are well known and used in the industry and not specific type or kind are required to practice this invention, but instead any one of a number of types, configurations and designs may be utilized. Furthermore the multiplexers 121 and 126 in the figure are mounted on the same horizontal plane as the DSX-1 jack assemblies 130 and 154, although they need not necessarily be.

[0047] In the preferred embodiment, the multiplexers 121 and 126 are M13's on printed circuit boards 122, which are mechanically and electrically connected to the rear or backplane printed circuit board assembly 123 with known connector technology (with no particular type being required to practice this invention), such as edge connectors 124 mounted on the backplane printed circuit board assembly 123.

[0048] In the preferred embodiment, there are active M13's and standby M13's. Since one M13 would handle the signals from all 28 circuits from a set of DSX-1 jack assemblies, only two multiplexers would actually be needed for operation on all fifty-six circuits. Rear or backplane printed circuit boards are generally known and the backplane printed circuit board assembly 123 will therefore not be described in further detail.

[0049] Figure 3 is a perspective view of an embodiment of this invention which includes fifty-six DSX-1 jack assemblies and four multiplexers, with two multiplexers being on each side of the first end of the cabinet framework, each pair representing an active multiplexer and a standby multiplexer, preferably for the DSX-1 jack assemblies located on that side of the cabinet framework.

[0050] Figure 3 illustrates an embodiment of a cabinet system which includes cabinet framework 150 with a first end 150a, a second end 150b, a top cover 150d, and side walls 150. This illustrates one of a number of different possible alternative configurations for this invention, with others also being contemplated by this invention. Figure 3 also illustrates a first set of DSX-1 jack assemblies 153 and a second set of DSX-1 jack

assemblies 154, and LED indicators 155 for the jack assemblies. A first set 151 of multiplexors being on one side of the cabinet framework 150 and a second set 152 of multiplexors being on the other side, each set representing an active and a standby multiplexor.

[0051] Figure 4 is a perspective view of one embodiment of a cabinet system contemplated by this invention, wherein DSX-3 assemblies are included within the integrated cabinet system. The DSX-3 assemblies may be included in place of or with DSX-1 assemblies, in combination with the M13's, within the contemplation of this invention. The item numbers are the same as for Figure 3, with the addition of the numbers identifying the DSX-3 assemblies. Other components are the same as those in Figure 3 and are therefore provided with the same numbers.

[0052] In this integrated cabinet, DSX-3 assemblies 162 & 163 are mounted within the cabinet and integrated with the DSX-1 jack assemblies and the M13's. Also shown in this alternative embodiment is an exterior DSX-3 160 mounted on the side wall of the cabinet and electrically connected to the backplane printed circuit board assembly (not shown in this Figure). DSX-3 assemblies generally include jacks 161 in a front or rear panel.

[0053] Figure 5 is a perspective view of an embodiment of this invention which includes DSX-1 jack assemblies and four multiplexers, the multiplexers being configured within the cabinet but above the DSX-1 assemblies. The like components from Figure 3 bear the same item numbers as the components in Figure 3. Figure 5 shows an alternative

integrated configuration contemplated by this invention wherein the multiplexers 151 and 152 are mounted in a horizontal orientation above the DSX-1 assemblies.

[0054] Figure 6 is a functional block diagram of the cabinet system components of one embodiment of a cabinet system contemplated by this invention, illustrating the patch/connect jack assemblies in block 202, switch assemblies 203 for the jack assemblies 202, and terminal pin connectors 201 for cross-connecting the jack assemblies. The cross-connect field may be wire-wrap pins or RJ-48 jacks, or others.

[0055] Figure 6 further illustrates active M13 in box 207, standby M13 in box 208, DS3 connectors on rear panel in block 209 electrically and operatively connected to the active M13 via connection 210. The "D" style or type connectors on the rear panel are electrically or operatively connected to the DSX-1 jack assemblies via connection 206. Figure 6 further illustrates the control, communications, indicates, alarms and power items in box 204, which may be preferred, but are not required to practice this invention.

[0056] It should also be noted that the foregoing depictions in Figure 6 are within block 219, which only represents two multiplexors and twenty-eight DSX-1 jack assemblies. In an embodiment of the invention which would include four multiplexors and fifty-six DSX-1 jack assemblies, a similar or identical block depiction would be shown in block 220. The active system would preferably be independent from the standby system, perhaps only sharing a ground stud. There would preferably be no shared

connections. The cross-connect field may be wire-wrap pins or RJ-48 jacks.

[0057] Figure 7 is a system block diagram of the cabinet system components of one embodiment of a cabinet system contemplated by this invention. Figure 7 shows the mirror systems, the first with an active multiplexer card 253 and the second mirror system with a standby multiplexer card 262. While the systems need not be identical, it is preferred that they be identical.

[0058] Figure 7 illustrates control, communications, indicates, alarms and power in boxes 250 and 263. These would include such aspects of the product as: initialization, configuration, provisioning, performance, monitoring, protection switching, and active/standby board control; ethernet and RS232 communications channels supporting SNMP, TL1 and craft interface protocols; alarm relays, status indicator, and ACO test push button; and power supplies.

[0059] The high speed channel blocks 251 and 261 (may also be referred to as high bandwidth) may preferably represent DS3 line interface units devices for copper or a fiber optic converter for optical applications, both of which are known in the art. The high speed/low speed multiplexer/demultiplexer blocks 252 and 262 multiplex the low speed channels into the high speed channel and the high speed channel into the low speed channel.

[0060] The low speed channel blocks, 254, 255, 264 and 265 may preferably be up to twenty-eight T1 lines or 21 E1 lines, or some

combination of the two. Block 256 represents T1, E1, DSX and/or "D" style or type super ribbons connectors on the backplane printed circuit board assembly.

[0061] Figure 8 is a diagram of the relationship of Figures 9 - 11, which comprise an electrical block diagrams of one embodiment of a cabinet system contemplated by the invention.

[0062] Figure 9 is an electrical block diagram of the cabinet system components of one embodiment of a cabinet system contemplated by this invention, as depicted in Figure 8. Figure 9 illustrates well known components utilized in printed circuit board assemblies, showing microprocessor 300 which may be any one of a number of different multi-processors, such as those made by Motorola, RS232 connection 304, Random Access Memory (RAM) 302, bus buffers address decoders 303, buffered address and data 309, ethernet connection 306, flash Read Only Memory ("ROM") 302 and LED ACO interface 307. It will be noted by those of ordinary skill in the art that there are numerous way a printed circuit board assembly may be conducted, assembled and/or arranged, within the contemplation of this invention, with no one in particular being required to practice this invention.

[0063] Figure 10 is an electrical block diagram of the cabinet system components of one embodiment of a cabinet system contemplated by this invention, as depicted in Figure 8. Figure 10 illustrates M13 310, T1 or E1 line interface units 311, and DS3 line interface unit 312.

[0064] Figure 11 is an electrical block diagram of the cabinet system components of one embodiment of a cabinet system contemplated by this invention, as depicted in Figure 8. Figure 11 illustrates some of the connections and other components, such as ethernet connection 315, RS232 (front) connection 316, relay alarms 317, DS3 connection 318, DSX-1 connection 319, "D" style or type connector 314.

[0065] Figure 12 is a perspective view of an embodiment of this invention which includes DSX-3 assemblies and four multiplexers, with two multiplexers being on each outward side of the first end of the cabinet framework. Figure 12 is similar to Figure 4 with like items being numbered the same as in Figure 4, and illustrates an embodiment of the invention wherein there are only DSX-3 assemblies combined with the M13's. Typically there are two DSX-3 assemblies for each M13 and the DSX-3 assemblies may be placed in a smaller area. For instance, the height of the cabinet framework 150 could be in the two to six inch range, with four inches being a typical height for the DSX-3 cabinet framework.

[0066] As will be appreciated by those of reasonable skill in the art, there are numerous embodiments to this invention, and variations of elements and components which may be used, all within the scope of this invention.

[0067] One embodiment of this invention for example involves a telecommunications cabinet assembly comprised of: a cabinet framework with a first end and a second end; a plurality of DSX-1 jack assemblies mounted on the cabinet framework, each jack assembly being comprised of:

a front panel portion which includes a single column of at least one sleeve for receiving a plug therein; a switch assembly support portion; and at least one switch assembly positioned within the framework rearward from the corresponding sleeve, the switch assembly being adapted to receive and make electrical contact with a plug inserted in the corresponding sleeve; and at least one multiplexer mounted on the cabinet framework and disposed to be accessed from the first end of the cabinet framework. In addition to the foregoing, this invention contemplates the following: a telecommunications cabinet assembly as recited above and further wherein the plurality of DSX-1 jack assemblies are each removably secured to the first end of the cabinet framework; a telecommunications cabinet assembly as stated above and further wherein the plurality of DSX-1 jack assemblies include at least forty-two DSX-1 circuits; a telecommunications cabinet assembly as stated above and further wherein the at least one multiplexer comprises an M13 multiplexer/demultiplexer; a telecommunications cabinet assembly as stated above and further comprising a backplane circuit board assembly electrically connected to the at least one multiplexer and the plurality of DSX-1 jack assemblies. Still further embodiments of this invention would include the telecommunications cabinet assembly as recited in the preceding paragraph and further including: at least one DSX-3 jack assembly mounted on the cabinet framework; or wherein the at least one multiplexer is mounted in the

same horizontal plane as the plurality of DSX-1 jack assemblies; or wherein the at least one multiplexer is comprised of one active and one standby multiplexer. The telecommunications cabinet assembly recited above may also be provided wherein the plurality of multiplexers comprise: a high speed transmission line interface unit responsible for signal input-output interface with a set of sending and receiving high speed transmission lines; a low speed transmission line interface unit responsible for signal input-output interface with a set of sending and receiving low speed transmission lines; and a multiplex converting unit for performing multiplexing and demultiplexing between high speed signals transmitted on the high speed transmission lines and low speed signals transmitted on the low speed transmission lines. In such a case the telecommunications cabinet assembly may be provided wherein the interface between the multiplex converting unit and the switch assemblies comprises an optical fiber interface.

[0068] As shown, embodiments of the telecommunications cabinet assembly further may include a backplane printed circuit board assembly mounted to the cabinet framework; and an interconnect printed circuit board electrically coupling the jack assemblies with the backplane printed circuit board assembly; or wherein the plurality of

jack assemblies are disposed to be accessed from the front end of the cabinet framework.

[0069] Another embodiment of the invention may be a telecommunications cabinet assembly comprised of: a cabinet framework with a first end and a second end, and wherein the framework defines a width dimension to a height dimension ratio which is greater than one; a plurality of DSX-1 jack assemblies mounted on the cabinet framework; and at least one multiplexer mounted on the cabinet framework. In such a case the cabinet framework may define the width dimension to height dimension ratio at greater than three and less than four, or in a range from 14 inches to 24 inches. The telecommunications cabinet assembly described above may also define the height dimension to be in a range from 3 inches to 6 inches.

[0070] In another embodiment of the invention, a telecommunications cabinet assembly may be provided which is comprised of: a cabinet framework with a first end and a second end, the cabinet framework configured to mount to a nineteen inch wide distribution rack; at least forty-two DSX-1 jack assemblies mounted on the cabinet framework; and at least two multiplexers mounted on the cabinet framework, the at least two multiplexers being electrically connected to the at least forty-two DSX-1 jack

assemblies. In such a telecommunications cabinet assembly, there may also be a backplane circuit board assembly electrically connected to the at least one multiplexer and the at least forty-two DSX-1 circuits.

[0071] Yet another embodiment of a telecommunications cabinet assembly contemplated by this invention may be comprised of: a cabinet framework with a first end and a second end; a plurality of DSX-1 jack assemblies mounted on the cabinet framework, each jack assembly being comprised of: a front panel portion which includes a single column of at least one sleeve for receiving a plug therein; a switch assembly support portion; and at least one switch assembly positioned within the framework rearward from the corresponding sleeve, the switch assembly being adapted to receive and make electrical contact with a plug inserted in the corresponding sleeve; at least one multiplexer mounted on the cabinet framework; and a backplane circuit board electrically connected to the at least one multiplexer and the plurality of DSX-1 jack assemblies. In such an embodiment, the telecommunications cabinet assembly may further involve the backplane circuit board assembly being electrically connected to the at least one multiplexer and the plurality of DSX-1 jack assemblies by a backplane interconnect conductor.

[0072] Another telecommunications cabinet assembly contemplated by this invention may be comprised of a cabinet framework with a first end and a second end, the cabinet framework having a vertical height of less than twelve inches, the cabinet framework including a first set of DSX-1 jack assemblies mounted on and disposed to be accessed from the first end of the cabinet framework, a first multiplexer mounted on and disposed to be accessed from the first end of the cabinet framework, the first multiplexer being electrically connected to the first set of DSX-1 jack assemblies; and wherein there is at least one multiplexer and at least twenty-eight DSX-1 jack assemblies mounted in the cabinet framework. This embodiment may further include the first multiplexer being electrically connected to the first set of DSX-1 jack assemblies through a backplane printed circuit board assembly, or wherein there are at least two multiplexers and at least fifty-six DSX-1 circuits mounted on the cabinet framework. In such a case, the vertical height may, but need not be, less than six inches. There may also be at least two multiplexers and at least fifty-six DSX-1 circuits mounted on the cabinet framework.

[0073] Another embodiment of a telecommunications cabinet assembly contemplated by this invention may be comprised of a cabinet framework with a first end and a second end, the cabinet

framework having a vertical height of less than twelve inches, the cabinet framework including a first set of DSX-1 jack assemblies mounted on the cabinet framework, a first multiplexer mounted on the cabinet framework, the first multiplexer being electrically connected to the first set of DSX-1 jack assemblies; and wherein the first multiplexer is mounted on a same horizontal plane within the cabinet as the first set of DSX-1 jack assemblies.

[0074] In yet another embodiment, a telecommunications cabinet assembly may be comprised of: a cabinet framework with a first end and a second end; a plurality of DSX-3 assemblies mounted on the cabinet framework; and at least one multiplexer mounted on the cabinet framework and electrically connected to the plurality of DSX-3 assemblies. In this embodiment, DSX-1 assemblies would not be included.

[0075] In compliance with the statute, the invention has been described in language more or less specific as to structural and methodical features. It is to be understood, however, that the invention is not limited to the specific features shown and described, since the means herein disclosed comprise preferred forms of putting the invention into effect. The invention is, therefore, claimed in any of its forms or modifications within the proper scope of the

[illegible]